

電圧降下計算書(電灯)

物件名 程島商店

幹線NO	系統名	容量 (KVA)	電流 (A)	需要率 %	幹線 サイズ	電線太さ許 容電流(A)	分岐 開閉器	電線長さ (m)	分岐幹線の 接続	NO	主開閉器	主開閉器か らの変圧器	パンク NO	電圧降下 (V)
1	1L-1	50	250	100	100			54.05						2.405
7	L-R	50	250	100	60			16.7						1.239
17	ネオン	28.4	142	100	60			31.95						1.346
2	2L-1	15.8	79	100	38			59.85						2.215
9	IP盤	10	50	100	38			87.35						2.046
14	2L-2	30	150	100	60			77.35						3.442
6	1L-2	30	150	100	60			73.35						3.264
合計		214												